



PM5005 INTEGRATED AMPLIFIER



40 w x 2ch

CURRENT
FEEDBACK

SYSTEM
REMOTE

METAL
FRONT

BUS

A-B

MM
Phono

PURE
DIRECT

green standby
eco friendly

New to the Marantz collection, this excellent entry-level integrated amplifier breaks all the rules. That's because it's the first in its class to offer current feedback architecture – a feature that normally is reserved for the more expensive models. This technology provides very fast and accurate signal handling, which results in perfectly balanced stereo sound reproduction as well as a very open and precise sound stage. It's also been recently enhanced with performance-optimising discrete audio circuitry and fine-tuning components. In addition, this year's model looks a little more stylish than last year's, thanks to new elegant knob design. On top of that, it comes with a new remote and a new low-power stand-by and auto stand-by mode. But back to being an amp: the PM5005 offers 40W per channel into 8 ohm or 55W into 4 ohm, and includes a metal chassis and a front metal panel to ensure a very rigid and solid base. It also has a Phono MM equaliser, as well as a Source Direct functionality to ensure shortest signal paths. Without doubt, the PM5005 has raised the performance bar in the so-called entry level area. Great sound. Amazing versatility.

Main Features

- Integrated Current Feedback Amplifier with 2x 40W / 8 ohm rms
- Gold Plated Inputs/Outputs incl. Phono (MM) input
- Marantz proprietary HDAM-SA3 circuits
- Selected high quality audio components
- Fully discrete volume amplifier circuit
- Tone control and Source Direct function
- High quality Speaker Terminals (A / B switchable)
- Headphone output
- System remote to control Amplifier, CD-Player and Network Player

EAN

EU	PM5005/N1B	4951035053522	Black
	PM5005/N1SG	4951035053515	Silver-Gold

www.marantz.eu

because music matters

PM5005 INTEGRATED AMPLIFIER



FEATURES	PM5005
Channels	2
Current Feedback Topology	•
Phono EQ: Standard	•
HDAM version	SA3, SA2
Toroidal Power Transformer	•
High Grade Audio Components	•
Balance / Bass / Treble / Loudness	• / • / • / •
OTHERS	
Linear Drive Power Supply	•
Source Direct	•
Standby Mode	•
INPUTS / OUTPUTS	
Audio Inputs	6
Phono Input: MM	•
Audio Outputs	2
Gold Plated Cinch	•
Speaker A / B	•
Speaker Terminals:	Transparent, Screw type
Number of terminals	4
D-Bus	•
Headphone Out	•

SPECIFICATIONS	
Power Output (8 / 4 Ohm RMS)	40 W / 55 W
Frequency Response	10 Hz - 50 kHz
Total Harmonic Distortion	0.05 %
Damping Factor	100
Input Sensitivity: MM	2.2 mV / 47 kOhm
Signal to Noise Ratio: MM	83 dB
Input Sensitivity: High level	200 mV / 20 kOhm
Signal to Noise Ratio: High level	102dB (2V input)
GENERAL	
Available colors: Black / Silver-Gold	• / •
Metal Front Panel	•
Power Consumption	110 W
Standby Consumption	0.3 W
Auto Power off	•
Detachable Power Cable	•
Remote Control	RC002PMCD
System Remote Function	•
Maximum Dimensions (W x D x H)	440 x 370 x 105 mm
Weight	6.7 kg

Design and specifications are subject to change by Marantz without notice.

Perfect partner
CD5005



CD Player